

How to wire the switch in the distribution box



Overview

The cable or wire size, the rating of breakers, fuse, etc depends on the type of wiring, purpose, and rating of loads.

Key Takeaways

To wire a switch in a distribution box, connect the incoming phase and neutral to the main switch, then route power through protective devices to branch switches, ensuring proper earth and neutral connections.

Step-by-Step Wiring Process

1. Safety First Always turn off the main power supply before starting any wiring to prevent electric shock. Verify with a voltage tester that no live current is present.
2. Mount the Distribution Box Secure the distribution box to a wall at an accessible height, ensuring it is free from obstructions and moisture.
3. Identify Components

- Main Switch (MCB or DP MCB): Controls overall power.
 - RCCB/RCD: Provides protection against earth leakage.
 - Branch MCBs or switches: Protect individual circuits.
 - Busbars/Neutral/Earth links: Distribute power safely to all circuits .
4. Connect Incoming Supply
 - Connect the phase (live) wire to the input terminal of the main switch.

- Connect the neutral wire to the neutral link or input of the main switch if using a DP MCB .
- Connect the earth wire to the earth link or metallic body of the box. 5. Wiring Through Protective Devices
- From the output of the main switch, connect to the input of the RCCB.
- For branch circuits:
 - Single-pole MCBs: Connect only the phase wire from RCCB output to the MCB input; neutral goes to the neutral link.
 - Double-pole MCBs: Connect both phase and neutral from RCCB output to the MCB input . 6. Connect the Loads
- For each load, connect the phase wire to the output of the corresponding MCB.
- Connect the neutral wire to the neutral link and the earth wire to the earth link . 7. Organize and Secure Wires
- Use plastic ties to bind wires neatly, maintaining uniform spacing and avoiding kinks.
- Ensure wiring direction: left side for incoming connections, right side for outgoing circuits . 8. Testing and Safety Inspection
- After wiring, use a multimeter to check for continuity, correct voltage, and absence of short circuits.
- Verify that all connections are tight and that no exposed wires are present.
- Ensure the distribution box is not overloaded and all protective devices are rated appropriately for the load . Following these steps ensures that the switch and all circuits in the distribution box are wired safely and efficiently, providing reliable power distribution while minimizing the risk of electrical hazards.

Article Content

How to wire a DB – Distribution Board Wiring – Mechatrofice

The cable or wire size, the rating of breakers, fuse, etc depends on the type of wiring, purpose, and rating of loads. It

Related Video Reference

This video was associated with the source search result. Verify technical details against current product documentation and project requirements.

Contact Us

Continue your research online:

Website: <https://coetzerinvestments.co.za>

Technical inquiry: <https://coetzerinvestments.co.za/contact.html>

This document is for preliminary research. Verify specifications against current standards, product documentation and project requirements.

